

Saferinse 2000

Product Code: SRI

PRODUCT DESCRIPTION

An aqueous deionised solvent blend which removes any solubilised residues after cleaning printed circuit board assemblies with **Electrolube Safewash 2000 (SWA)**. **Saferinse 2000** is 100% Ozone Friendly.

Customers wanting to rinse larger quantities of PCBs should refer to **Electrolube De-Ionised Water**, Order Code **DEI**. This product is designed for use within the electronics industry and is available in 1 and 5 litre containers. A separate Technical Data Sheet is available for this product.

PRODUCT USE

Cleaning remaining residues from PCB's after cleaning with 100% ozone friendly **Safewash 2000**.

FEATURES

- * 100% Ozone Friendly
- * Biodegradable
- * Low corrosivity
- * Non-flammable
- * Very low toxicity

TYPICAL PROPERTIES

Boiling Point	100°C
Specific Gravity (25°C)	1
Viscosity (25°C)	20 cP
Inhalation Toxicity	400 ppm
Flash Point	None

TECHNICAL
DATA
SHEET



Copyright Electrolube 2003

All information is given in good faith but without warranty. Properties are given as a guide only and should not be taken as a specification. Electrolube cannot be held responsible for the performance of its products within any application determined by the customer, who must satisfy themselves as to the suitability of the product.



Saferinse 2000 – Page 2

DIRECTIONS FOR USE

Hold the PCB at approx. 45°. Spray **SRI** generously onto the assembly and allow to run down the board. The PCB may be quickly dried using **Electrolube non-CFC Airduster (EAD)**.

PACKAGING

400 ml Aerosol

ORDER CODE

SRI400H

TECHNICAL
DATA
SHEET



Copyright Electrolube 2003

All information is given in good faith but without warranty. Properties are given as a guide only and should not be taken as a specification. Electrolube cannot be held responsible for the performance of its products within any application determined by the customer, who must satisfy themselves as to the suitability of the product.

